



**Diesel Generator
Sales, Installation,
Hire, Spares, Service
& Refurbishment**



Certificate No: 1152

3.5kVA Honda Petrol Generator	Model YH3.5ES
--------------------------------------	----------------------

GENERAL	
OUTPUT RATINGS	
50Hz, 230 VOLT, SINGLE PHASE	
Prime Rating	3.5kVA 2.8kW 1500 RPM
ENGINE MAKE	Honda
ENGINE MODEL	GX 200



TECHNICAL DATA			
Engine Model	GX 200	Protection Class	IP23
Start	Recoil	Insulation Class	H
Frequency	50Hz	Fuel Cons: (l/hr)	1.3
Volts	230	Sound Attenuation	81 Dba @ 1M
Oil Capacity	0.6 Litres	Alternator Type	Without collar or brush
Fuel Tank Capacity	12 Litres	Regulation	Mechanical

DIMENSIONS AND WEIGHTS				
Length Cm	Width Cm	Height Cm	Dry Weight Kg	Fuel Tank Size Litres
57	45	46	46	3.6

HONDA

Registered Office:
Yorpower Limited
Electricity Building
Blenheim Road
Pocklington Industrial Estate
York, YO42 1NR
UNITED KINGDOM



T: +44 (0) 1759 305400
F: +44 (0) 1759 305405
E: sales@yorpower.com
W: www.yorpower.com

Yorpower Limited, Registered in England and Wales No. 7035780