



**Diesel Generator
Sales, Installation,
Hire, Spares, Service
& Refurbishment**



Certificate No: 1152

Model YH5PTRL - 5kVA Honda Petrol Generator

GENERAL

OUTPUT RATINGS

50Hz, 230 VOLT, SINGLE PHASE

Prime Rating 5kVA 4kW 1500 RPM

ENGINE MAKE Honda

ENGINE MODEL GX 270



TECHNICAL DATA

Engine Model	GX 270	Protection Class	IP23
Start	Recoil	Insulation Class	H
Frequency	50Hz	Fuel Cons: (l/hr)	2.1
Volts	230	Sound Attenuation	81 Dba @ 1M
Oil Capacity	1.1 Litres	Alternator Type	Without collar or brush
Fuel Tank Capacity	12 Litres	Regulation	Mechanical

Rating Definitions

Prime power: No limitation to annual hours of operation and these models can supply 10% overload for 1 in 12 hours.

Standby power: Ratings only applicable for supplying power in event of power failure. No overload is permitted on these ratings.

DIMENSIONS AND WEIGHTS

Length Cm	Width Cm	Height Cm	Dry Weight Kg	Fuel Consumption L/hr
71.5	57	49	64	2.1

HONDA

Registered Office:
Yorpower Limited
Electricity Building
Blenheim Road
Pocklington Industrial Estate
York, YO42 1NR
UNITED KINGDOM



T: +44 (0) 1759 305400
F: +44 (0) 1759 305405
E: sales@yorpower.com
W: www.yorpower.com